

# Torridon USB 3.0 Cable Pull Module



---

Hot-Swap automation for USB 1.1/2.0/3.0 cables

---



## Reduce Time to Market

Cut time to market by 20% for new products by automating manual test procedures

## Reduce Capital Costs

Faster and more detailed testing with Torridon means fewer test systems are required in the lab

## Reduce Human Error

Removing human intervention during tests increases consistency and results in far fewer mistakes. Test scripting provides logging and 100% repeatability

## Increase Product Reliability

Advanced techniques, such as bounds testing and fault injection provide a higher level of confidence and reduced field returns

### **Torridon Cable Pull Modules:**

Automated solution for Cable Pull / Push and Fault Injection. Cable Pull Modules vastly reduce test duration and introduce a level of repeatability and precision that is impossible during manual tests.

### **Complete Automation:**

Any test that requires manual intervention to pull or plug a cable can now be fully automated.

### **Simple Integration:**

The Torridon System works with your existing automated test setup and integrates with minimal effort. A simple command set allows for easy scripting. Quarch provides full support as standard while you get started

### **Who Can Benefit?**

Silicon Manufacturers  
Firmware/Driver Designers  
Hardware Qualification Labs  
System Integrators

# Torridon USB 3.0 Cable Pull Module

## Interface Specification

### Power

- ▶ Supplied from Torridon Interface Card or Array Controller

### Comms

- ▶ USART Serial - DB9
- ▶ USART Serial - RJ45(RS232D)
- ▶ USB

## Cable Compatibility

### Types

- ▶ USB-B host connection
- ▶ USB-A device connection

### Speeds

- ▶ Low Speed, Full Speed, High Speed, Super Speed.

## Switching

### Switches

- ▶ High Speed RF switches
- ▶ Low insertion loss

### Switched Pins

- ▶ All Power/Data Pins may be switched individually

## Physical Dimensions

### QTL1309

- ▶ Length 84.0 mm
- ▶ Width 63.5 mm
- ▶ Height 30.0 mm

## Timing Specification

### Timers

- ▶ 6 Independent timers for multi stage hot-swap

### Timing resolution

- ▶ 1mS

### Pin-bounce resolution

- ▶ 10uS

### Pin-bounce modes

- ▶ Constant Frequency
- ▶ User defined 100 bit pattern

### Manual Mode

- ▶ Full manual connection control for fault injection and bugged hardware generation

## Glitching

### Timing

- ▶ Glitch any combination of signals with pulses down to 50nS

### Sequences

- ▶ Run glitches in sequences and PRBS patterns

## Fault Injection

### USB Errors

- ▶ Create Data / Power Failures
- ▶ Fault individual pins
- ▶ Fault all pins
- ▶ Create intermittent disruptions

## Support and Utilities

Phone and email support direct to the engineers as standard

'TestMonkey' GUI for rapid test prototyping, script generation and bench testing

## Ordering Information

QTL1309 - Single Port Unit

### Single units

- ▶ Ideal for bench testing, debugging and evaluation

### Multiple units

- ▶ Run from a Torridon Array Controller for synchronized testing of many cables

## Quarch Technology Ltd

### UK Sales / Technical Enquiries

+44 1343 508 140

enquiries@quarch.com

### US Sales Office

+1 617 245 0528

us\_enquiries@quarch.com

<http://www.quarch.com>